SIIT ITS323

ITS323 – Quiz 3

Name:		
ID.	M 1	(, (10)
ID:	Mark:	(out of 10)

Question 1 [3 marks]

In a wireless communications system a source transmits with power 5dBm. Both transmit and receive antenna gains are 12dBi. If the path loss between antennas is measured to be 90dB, what is the received power?

Question 2 [1 marks]

What is the name of the encoding scheme that varies the amplitude of the input carrier signal as the input analog data changes?

Question 3 [3 marks]

a) A transmitter adds a 1-bit even parity bit to the front (left-most position) of the 8-bits of data 01101010. If the last two bits (right-most position) is in error, what does the receiver do? (e.g. is an error detected – why? Or not detected – why?) [2 marks]

b) Using this error-detection scheme and assuming no errors, what is the throughput for a link with data rate 4.5Mb/s? [1 mark]

SIIT ITS323

Question 4 [3 marks]

If 32-bit, 20kHz PCM is used to encoded a single-channel 5 minute song, how long will it take to send this song to your friend's computer if the computers are linked via 100Mb/s Ethernet?