ITS 323 – QUIZ 3 (ITA)

First name: _____

Last name: _____

ID: _____

Total Marks: _____

out of 10

Question 1 [3 marks]

An error correcting code maps 2-bits of data into a 4 bit codeword according to the following scheme:

- 00 => 1001
- 01 => 0111
- 10 => 1011
- 11 => 1100

The Hamming distance is used to correct errors.

For the following received codewords, indicate what the receiver does. That is, either:

- Assumes NO ERROR;
- Successfully DETECTs and CORRECTs error;
- DETECT ONLY, but cannot correct;

If NO ERROR or DETECT/CORRECT, indicate the received data.

a) 0110	NO ERROR	DETECT/CORRECT	DETECT ONLY
	Received Data:		

b) 1011	NO ERROR	DETECT/CORRECT	DETECT ONLY
	Received Data:		

c) 0011	NO ERROR	DETECT/CORRECT	DETECT ONLY
	Received Data:		

Question 2 [2 marks]

Draw the analog signal used to transmit the digital data below if Amplitude Shift Keying is used.

	0	0	1	0	0	1	1	1	0	1	0	1
0V												

Question 3 [2 marks]

A single bit even parity check is applied to an 8-bit data frame. For the following cases of errors, indicate if the receiver can detect the error or not (circle the answer):

a)	The last bit of the data frame is in error	DETECT	NOT DETECT
b)	The last two bits of the data frame are in error	DETECT	NOT DETECT
c)	The last three bits of the data frame are in error	DETECT	NOT DETECT
d)	The parity bit is in error	DETECT	NOT DETECT

Question 4 [3 marks]

What is the maximum throughput of the Stop and Wait Flow Control protocol.

You can assume:

- Data rate is 1Mb/s
- Data frame size is 5,000 bits
- ACK size is 100 bits
- Propagation time is 15msec
- No processing delay