SIIT ITS 323

## ITS 323 – DATA TRANSMISSION EXAMPLES

### 1 Bit Rates

### What is the bit rate for high-definition TV (HDTV)?

HDTV uses digital signals to broadcast high quality video signals. The HDTV screen is normally a ratio of 16: 9. There are 1920 by 1080 pixels per screen, and the screen is renewed 30 times per second. 24 bits represents one colour pixel.

Bits per second =  $1920 \times 1080 \times 30 \times 24 = 1492992000 = 1.5$ Gb/s

The TV stations reduce this rate to 20 to 40 Mbps through compression.

# 2 Nyquist Theorem

#### Example 3.3 from Stallings, page 80

Consider a voice channel being used, via modem, to transmit digital data. Assume a bandwidth of B = 3100Hz. Then the Nyquist capacity, C, of the channel is:

$$C = 2B = 2 \times 3100 = 6200 \text{b/s}$$

If we now assume M = 8, a value used for some modems, then  $C = 2 B \log M = 2B \times 3 = 18600b/s$ .

## 3 Shannon Capacity

#### Example 3.4 from Stallings, page 81

Suppose the spectrum of a channel is between 3MHz and 4MHz (hence bandwidth of 1MHz) and the SNR = 24dB.

Then absolute SNR =  $10^{(24/10)} = 251$ 

Using Shannon's formula:

$$C = 1MHz \log_2 (1 + SNR) = 106 x = 8 x 106 = 8Mb/s$$

This is a theoretical limit, but if we assume we can reach it, then how? Nyquists theorem also tells us:

$$C = 2B \log_2(M)$$

So  $8Mb/s = 2 \times 1MHz \times log_2(M)$ 

So we need M = 16

That is, our signal needs to be able to carry 16 different levels.